查询ADM1486供应商

+5 V Low Power RS-485 PROFIBUS Transceiver

Preliminary Technical Data — ADM1486

FEATURES
Meets & Exceeds EIA RS-485 & EIA RS-422 Standard
50 Mb/s Data Rate
Recommended for PROFIBUS Applications
2.1V Minimum Differential Output with 54Ω Termination
Low Power 0.5mA I_{CC}
Thermal Shutdown & Short Circuit Protection
Zero Skew Driver & Receiver
Driver Propagation Delay: 8 ns
Receiver Propagation Delay: 12 ns
High Z Outputs with Drivers Disabled or Power Off
Superior Upgrade for SN65ALS1176
15kV HBM ESD Protection on I/O Pins A & B
Available in Standard 8-pin SOIC & Miniature 8-pin Micro SOIC packages

APPLICATIONS
Industrial Field Equipment

FUNCTIONAL BLOCK DIAGRAM



GENERAL DESCRIPTION

The ADM1486 is a differential line transceiver suitable for high speed bidirectional data communication on multipoint bus transmission lines. It is designed for balanced data transmission, complies with EIA Standards RS-485 and RS-422 and is recommended for PROFIBUS applications. The part contains a differential line driver and a differential line receiver. Both the driver and the receiver may be enabled independently. When disabled or with power off, the driver outputs are tristated.

The ADM1486 operates from a single +5 V power supply. Excessive power dissipation caused by bus contention or by output shorting is prevented by a thermal shutdown circuit. This feature forces the driver output into a high impedance state if during fault conditions a significant temperature increase is detected in the internal driver circuitry.

Up to 50 transceivers may be connected simultaneously on a bus, but only one driver should be enabled at any time. It is important therefore that the remaining disabled drivers do not load the bus. To ensure this, the ADM1486 driver features high output impedance when disabled and also when powered down.

This minimizes the loading effect when the transceiver is not being utilized. The high impedance driver output is maintained over the entire common-mode voltage range from –7 V to +12 V.

The receiver contains a fail safe feature which results in a logic high output state if the inputs are unconnected (floating).

The ADM1486 is fabricated on BiCMOS, an advanced mixed technology process combining low power CMOS with fast switching bipolar technology. All inputs and outputs contain protection against ESD; all driver outputs feature high source and sink current capability. An epitaxial layer is used to guard against latch-up.

The ADM1486 features extremely fast switching speeds. Minimal driver propagation delays permit transmission at data rates up to 50 Mbits/s while low skew minimizes EMI interference.

The part is fully specified over the commercial and industrial temperature range and is available in an 8-lead DIL/SOIC/μSOIC package.

REV Pr. B

Information furnished by Analog Devices is believed to be accurate and reliable. However, no responsibility is assumed by Analog Devices for its use, nor for any infringements of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Analog Devices.

One Technology Way, P.O. Box 9106, Norwood, MA 02062-9106, U.S.A.
Tel: 781/329-4700 World Wide Web Site: http://www.analog.com
Fax: 781/326-8703
© Analog Devices, Inc., 2000

ADM1486–SPECIFICATIONS (V_{CC} = +5 V ± 5%. All specifications T_{MIN} to T_{MAX} unless otherwise noted.)

Parameter	Min	Typ	Max	Unit	Test Conditions/Comments
DRIVER					
Differential Output Voltage, V_{OD}			5.0	V	R = Infinity, Figure 1
	2.0		5.0	V	V_{CC} = 5 V, R = 50 Ω (RS-422), Figure 1
	2.1		5.0	V	R = 27 Ω (RS-485), Figure 1
V_{OD3}	2.1		5.0	V	V_{TST} = –7 V to +12 V, Figure 2
$\Delta\|V_{OD}\|$ for Complementary Output States			0.2	V	R = 27 Ω or 50 Ω, Figure 1
Common-Mode Output Voltage V_{OC}			3	V	R = 27 Ω or 50 Ω, Figure 1
$\Delta\|V_{OD}\|$ for Complementary Output States			0.2	V	R = 27 Ω or 50 Ω
Output Short Circuit Current(V_{OUT}=High)	60		150	mA	–7 V ≤ V_O ≤ +12 V
Output Short Circuit Current(V_{OUT}=Low)	60		150	mA	–7 V ≤ V_O ≤ +12 V
CMOS Input Logic Threshold Low, V_{INL}			0.8	V	
CMOS Input Logic Threshold High, V_{INH}	2.0			V	
Logic Input Current (DE, DI)			±1.0	µA	
RECEIVER					
Differential Input Threshold Voltage, V_{TH}	–0.2		+0.2	V	–7 V ≤ V_{CM} ≤ +12 V
Input Voltage Hysteresis, ΔV_{TH}		70		mV	V_{CM} = 0 V
Input Resistance	20			kΩ	–7 V ≤ V_{CM} ≤ +12 V
Input Current (A, B)			+ 1	mA	V_{IN} = 12 V
			–0.8	mA	V_{IN} = –7 V
Logic Enable Input Current ($\overline{RE}$)			±1	µA	
CMOS Output Voltage Low, V_{OL}			0.4	V	I_{OUT} = +4.0 mA
CMOS Output Voltage High, V_{OH}	4.0			V	I_{OUT} = –4.0 mA
Short Circuit Output Current	7		85	mA	V_{OUT} = GND or V_{CC}
Tristate Output Leakage Current			±1.0	µA	0.4 V ≤ V_{OUT} ≤ +2.4 V
POWER SUPPLY CURRENT					
I_{CC} (Outputs Enabled)		1.2	2.0	mA	Outputs Unloaded, Digital Inputs = GND or V_{CC}
I_{CC} (Outputs Disabled)		0.9	1.5	mA	Outputs Unloaded, Digital Inputs = GND or V_{CC}

Specifications subject to change without notice.

TIMING SPECIFICATIONS (V_{CC} = +5 V ± 5%. All specifications T_{MIN} to T_{MAX} unless otherwise noted.)

Parameter	Min	Typ	Max	Unit	Test Conditions/Comments
DRIVER					
Propagation Delay Input to Output T_{PLH}, T_{PHL}	4	8	15	ns	R_L Diff = 54 Ω C_{L1} = C_{L2} = 100 pF, Figure 3
Driver O/P to O/P T_{SKEW}		0	2	ns	R_L Diff = 54 Ω C_{L1} = C_{L2} = 100 pF, Figure 3
Driver Rise/Fall Time T_R, T_F		5	10	ns	R_L Diff = 54 Ω C_{L1} = C_{L2} = 100 pF, Figure 3
Driver Enable to Output Valid		8	15	ns	
Driver Disable Timing		8	15	ns	
RECEIVER					
Propagation Delay Input to Output T_{PLH}, T_{PHL}		8	12	20	ns C_L = 15 pF, Figure 5
Skew $\|T_{PLH}–T_{PHL}\|$		0	2	ns	
Receiver Enable T_{EN1}		5	10	ns	Figure 6
Receiver Disable T_{EN2}		5	10	ns	Figure 6

Specifications subject to change without notice.

ABSOLUTE MAXIMUM RATINGS*

(T_A = +25°C unless otherwise noted)

V_{CC} ..... +7 V
Inputs
Driver Input (DI) .....–0.3 V to V_{CC} + 0.3 V
Control Inputs (DE, RE) .....–0.3 V to V_{CC} + 0.3 V
Receiver Inputs (A, B) ..... –9 V to +14 V
Outputs
Driver Outputs ..... –9 V to +14 V
Receiver Output .....–0.5 V to V_{CC} + 0.5 V
Power Dissipation 8-Lead DIP ..... 500 mW
θ_{JA}, Thermal Impedance ..... +130°C/W
Power Dissipation 8-Lead SOIC ..... 450 mW
θ_{JA}, Thermal Impedance ..... +170°C/W
Power Dissipation 8-Lead Cerdip ..... 500 mW
θ_{JA}, Thermal Impedance ..... +125°C/W
Power Dissipation 8-Lead µSOIC ..... mW
θ_{JA}, Thermal Impedance .....+°C/W
Operating Temperature Range
Commercial (J Version) .....0°C to +70°C
Industrial (A Version) .....–40°C to +85°C
Storage Temperature Range .....–65°C to +150°C
Lead Temperature (Soldering, 10 sec) .....+300°C
Vapor Phase (60 sec) .....+215°C
Infrared (15 sec) .....+220°C

*Stresses above those listed under Absolute Maximum Ratings may cause permanent damage to the device. This is a stress rating only; functional operation of the device at these or any other conditions above those listed in the operational sections of this specification is not implied. Exposure to absolute maximum ratings for extended periods of time may affect device reliability.

Table I. Transmitting

	INPUTS		OUTPUTS	
$\overline{R}$ DE	DE	DI	B	A
X	1	1	0	1
X	1	0	1	0
X	0	X	Z	Z

Table II. Receiving

	INPUTS		OUTPUT
$\overline{R}$ DE	DE	A-B	RO
0	0	≥+0.2 V	1
0	0	≤ –0.2 V	0
0	0	Inputs Open	1
1	0	X	Z

PIN FUNCTION DESCRIPTION

Pin	Mnemonic	Function
1	RO	Receiver Output. When enabled if A >B by 200 mV, then RO = High. If A < B by 200 mV, then RO = Low.
2	$\overline{RE}$	Receiver Output Enable. A low level enables the receiver output, RO. A high level places it in a high impedance state.
3	DE	Driver Output Enable. A high level enables the driver differential outputs, A and B. A low level places it in a high impedance state.
4	DI	Driver Input. When the driver is enabled a logic Low on DI forces A low and B high while a logic High on DI forces A high and B low.
5	GND	Ground Connection, 0 V.
6	A	Noninverting Receiver Input A/Driver Output A.
7	B	Inverting Receiver Input B/Driver Output B.
8	V_{CC}	Power Supply, 5 V ± 5%.

PIN CONFIGURATION



ORDERING GUIDE

Model	Temperature Range	Package Option
ADM1486JN	0°C to +70°C	N-8
ADM1486JR	0°C to +70°C	SO-8
ADM1486AN	–40°C to +85°C	N-8
ADM1486AR	–40°C to +85°C	SO-8
ADM1486ARM	-40°C to +85°C	RM-8
ADM1486AQ	–40°C to +85°C	Q-8

CAUTION

ESD (electrostatic discharge) sensitive device. Electrostatic charges as high as 4000 V readily accumulate on the human body and test equipment and can discharge without detection. Although the ADM1486 features proprietary ESD protection circuitry, permanent damage may occur on devices subjected to high-energy electrostatic discharges. Therefore, proper ESD precautions are recommended to avoid performance degradation or loss of functionality.

Test Circuits



Figure 1. Driver Voltage Measurement Test Circuit



Figure 2. Driver Voltage Measurement Test Circuit 2



Figure 3. Driver Propagation Delay Test Circuit



Figure 4. Driver Enable/Disable Test Circuit



Figure 5. Receiver Propagation Delay Test Circuit



Figure 6. Receiver Enable/Disable Test Circuit

Switching Characteristics



Figure 7. Driver Propagation Delay, Rise/Fall Timing



Figure 8. Driver Enable/Disable Timing



Figure 9. Receiver Propagation Delay



Figure 10. Receiver Enable/Disable Timing



Figure 11. Typical RS-485 Network

Table III. Comparison of RS-422 and RS-485 Interface Standards

Specification	RS-422	RS-485	PROFIBUS
Transmission Type	Differential	Differential	Differential
Maximum Cable Length	4000 ft.	4000 ft.	-
Minimum Driver Output Voltage	±2 V	±1.5 V	±2.1 V
Driver Load Impedance	100Ω	54Ω	54Ω
Receiver Input Resistance	4 kΩ min	12 kΩ min	200 kΩ min
Receiver Input Sensitivity	±200 mV	±200 mV	±200 mV
Receiver Input Voltage Range	–7 V to +7 V	–7 V to +12 V	–7 V to +12 V
No of Drivers/Receivers Per Line	1/10	32/32	50/50

APPLICATIONS INFORMATION

Differential Data Transmission

Differential data transmission is used to reliably transmit data at high rates over long distances and through noisy environments. Differential transmission nullifies the effects of ground shifts and noise signals which appear as common-mode voltages on the line. There are two main standards approved by the Electronics Industries Association (EIA) which specify the electrical characteristics of transceivers used in differential data transmission.

The RS-422 standard specifies data rates up to 10 MBaud and line lengths up to 4000 ft. A single driver can drive a transmission line with up to 10 receivers.

In order to cater for true multipoint communications, the RS-485 standard was defined. This standard meets or exceeds all the requirements of RS-422 but also allows for up to 32 drivers and 32 receivers to be connected to a single bus. An extended common-mode range of –7 V to +12 V is defined. The most significant difference between RS-422 and RS-485 is the fact that the drivers may be disabled thereby allowing more than one (32 in fact) to be connected to a single line. Only one driver should be enabled at time, but the RS-485 standard contains additional specifications to guarantee device safety in the event of line contention.

Cable and Data Rate

The transmission line of choice for RS-485 communications is a twisted pair. Twisted pair cable tends to cancel common-mode noise and also causes cancellation of the magnetic fields generated by the current flowing through each wire, thereby, reducing the effective inductance of the pair.

The ADM1486 is designed for bidirectional data communications on multipoint transmission lines. A typical application showing a multipoint transmission network is illustrated in Figure 11. An RS-485 transmission line can have as many as 32 transceivers on the bus. Only one driver can transmit at a particular time but multiple receivers may be enabled simultaneously.

As with any transmission line, it is important that reflections are minimized. This may be achieved by terminating the extreme ends of the line using resistors equal to the characteristic impedance of the line. Stub lengths of the main line should also be kept as short as possible. A properly terminated transmission line appears purely resistive to the driver.

Thermal Shutdown

The ADM1486 contains thermal shutdown circuitry which protects the part from excessive power dissipation during fault conditions. Shorting the driver outputs to a low impedance source can result in high driver currents. The thermal sensing circuitry detects the increase in die temperature and disables the driver outputs. The thermal sensing circuitry is designed to disable the driver outputs when a die temperature of 150°C is reached. As the device cools, the drivers are re-enabled at 140°C.

Propagation Delay

The ADM1486 features very low propagation delay ensuring maximum baud rate operation. The driver is well balanced ensuring distortion free transmission.

Another important specification is a measure of the skew between the complementary outputs. Excessive skew impairs the noise immunity of the system and increases the amount of electromagnetic interference (EMI).

Receiver Open-Circuit Fail Safe

The receiver input includes a fail-safe feature which guarantees a logic high on the receiver when the inputs are open circuit or floating.

OUTLINE DIMENSIONS

Dimensions shown in inches and (mm).

8-Lead SOIC (SO-8)



8-Lead Plastic DIP (N-8)



8-Lead Cerdip (Q-8)



OUTLINE DIMENSIONS

Dimensions shown in inches and (mm).

8-Lead μSOIC (RM-8)